


# Markov Random Fields and Gibbs Sampling for Image De-noising

Chang Yue

Electrical Engineering, Stanford University

## Motivation

- High-order MRFs are more expressive.
- Filters like Gaussian blur are deterministic. Gradient ascent needs careful initialization and converges to suboptimal. Gibbs Sampling provides exploration, and does not require sophisticated initialization.
- There might be some patterns that pixels within a window tend to show.



## New Technique

- Tested different neighbor sizes, found that using 9 neighbors (3×3) is generally better than using 5 (pairwise) or 25 (5×5).
- Define energy as loss + prior + score.
- $E(Y_{ij}) = \sum_{X \in N(Y_{ij})} \|Y_{ij} - X\|_{n_1}^{n_1} + \lambda \sum_{Z \in N(Y_{ij}) \setminus X_{ij}} \|Y_{ij} - Z\|_{n_2}^{n_2} + \beta \psi(Y_{ij})$ .
- For loss,  $L_1$  norm has higher PSNR, but  $L_2$  norm has better visualization. Lorentzian is robust to outliers, and can provide smoothing.
- Applied sparse gradient and close-to-mean-of-neighbors priors.
- With the assumption that pixels within a window tend to have some patterns, defined 'score' as the dot product of patterns (filters) and pixels in window.
- By using first  $n$  principal components as filters and weighting dot products by variance explained, found that 'close to center' prior gives improvements.

## Related Work

- MRF:  $p(Y_{ij}) = \frac{1}{Z} \exp(-E(Y_{ij}))$ .
- Metropolis-Hastings for Markov Chain Monte Carlo.  $A(x'|x) = \min\left(1, \frac{P(x')Q(x|x')}{P(x)Q(x'|x)}\right)$ .
- Ising, Potts, hierarchical MRF models.
- Roth & Black: Fields of experts for learning image priors.
- McAuley et al: High-order MRF priors of color image.
- Barbu: Active Random Fields.

## Experimental Results

|              | Noisy    | Gaussian | $L_1$ norm. | $L_2$ norm | Lorentzian | filters  |
|--------------|----------|----------|-------------|------------|------------|----------|
| $\sigma=50$  |          |          |             |            |            |          |
|              | 14.78 dB | 23.53 dB | 25.94 dB    | 25.50 dB   | 25.76 dB   | 26.30 dB |
| $\sigma=100$ |          |          |             |            |            |          |
|              | 10.26 dB | 18.55 dB | 23.34 dB    | 21.08 dB   | 23.85 dB   | 24.46 dB |