

HOW GLONASS FAILED FOR 11 HOURS AND MULTI-GNSS SURVIVED



Frank van Diggelen,
Stanford PNT
29 Oct 2014
v1.4



but first ...


THE FIRST GPS MOOC

(5 minutes, followed by advertised talk)

Frank van Diggelen, Per Enge

WHAT'S A MOOC? "MASSIVE OPEN ONLINE COURSE"


- Free online course
- Video-lectures, interactive quizzes
- Pioneered at Stanford (Sebastian Thrun)
- Udacity, EdX, Coursera



Stanford

GPS: An Introduction to Satellite Navigation, with an interactive Worldwide Laboratory using Smartphones

Explore the fundamentals of the Global Positioning System (GPS) and how it works by conducting "backyard" laboratory experiments on your own mobile device. Learn the basics of satellite navigation and witness the power of a network with planet-wide coverage. Gain a deeper understanding of GPS and its role in our lives, while interacting with a worldwide community of learners and backyard scientists.



Instructors




Per Enge
Stanford University




Frank van Diggelen
Stanford University

GPS MOOC Registration: 24,000 people from 182 countries.



© Frank van Diggelen, October 2014





Gender & Age


Your course

All Coursera

Female Male



% Representation of Women in GPS MOOC, by birth decade



Labs, carried out worldwide, using smartphones

Stanford
GPS MOOC



GPS Worldwide Lab A (multipath)

First, in an open area away from buildings, you will record your GPS position. Then in another location, this time in a city or town, in a place with many buildings, record a new GPS position and again note the error.

All instructions are posted at: <http://www.gps-lab.org/labs.html> in Quiz Format before you submit here.

* Required

What was the error when you took the GPS reading in an open area?
Estimate the error, by comparing what your GPS shows in "map view" to what you know the location is.

- 0 - 2 meters
- 2 - 5 meters
- 5 - 10 meters
- 10 - 20 meters
- 20 - 50 meters
- 50 - 100 meters
- 100 - 200 meters
- Over 200 meters

GPS Worldwide Lab B (satellite visibility)

Go outside when one of these two satellites passes close to your location, and note the satellite elevation that you observe.

All instructions are posted at: www.gps-lab.org/labs.html. Be sure to first submit your answer in Quiz Format before you submit here.

* Required

Which GPS satellite did you see *

Pick one of the two specified in the lab (if you see both, pick the one that is higher in the sky).

- Satellite 4
- Satellite 18

Highest observed elevation for this satellite, in degrees *

- 90
- 80
- 70
- 60
- 50
- 40
- 30 or lower

Your Latitude *

Enter degrees and decimals (e.g. 37.893), excluding the letter N or S.

GPS Worldwide Lab C (signal strength)

Measure C/No value outside, and indoors. Estimate the RF losses of your receiver by comparing the C/No value outdoors to the C/No value indoors. The difference is the RF losses through the building.

All instructions are posted at: www.gps-lab.org/labs.html. Be sure to first submit your answer in Quiz Format before you submit here.

* Required

Enter the average C/No value of the strongest three satellites, outdoors (Units: dB-Hz).

See the lab instructions for help.

Compute the RF losses, compared to our nominal design (Units: dB). This is the difference between the C/No value outdoors and indoors. See the lab description. *

$x = 45 - (\text{average outdoor C/No entered above})$

Enter the average C/No value of the strongest three satellites, indoors (Units: dB-Hz).

If your receiver does not track three satellites, enter zero.




HOW GLONASS FAILED FOR 11 HOURS AND MULTI-GNSS SURVIVED



Frank van Diggelen,
Stanford PNT
29 Oct 2014

PROBLEMS WORLDWIDE:



Altus Positioning: “we are experiencing calls from customers *all over the world*, experiencing GLONASS outages”

“all over the world”, GPS/GLO receivers

Seoul, S. Korea, GPS/GLONAS

HERS		98788876776557667677878*	98898887788768777577887988998889888878776799*89*
HERT		*98*998788867777667788889888888787878887778889899879887778788899*999	
HLFX		666666777866786787778777666677878789978*9888765566665877878987	----22-1
HNPT		8666666677678787798888797666776677989988**99998866666767788998999*888888	
HOB2		889888799978988877768778887888799867888776666666777998798967877766667667	
HOFN		9***9999*9989987887998999999999*98***9998*87988999*999**98*99	----23335
		+	+
		0	24

GLONASS satellites tracked by IGS receivers (from CODE analysis protocol of April 1). **Some receivers unaffected, some stopped tracking GLONASS after 9^h p.m. (red line), some even stopped GPS tracking!**

Out of about 180 receivers used by CODE, about 60 were severely affected!


International Association of Geodesy



3-Jun-14

6

IGS, Worldwide: “Of 180 receivers, 60 severely affected




Harwich, England, GLONASS receiver

WHAT HAPPENED?

1. Incorrect ephemeris uploaded to all GLONASS satellites:

xyz	× Bad
clock	✓ Good



2. No unhealthy flags set
3. Persisted for 11 hours



- **LTO = Long Term Orbits**
 - for GPS, GLO, QZS, BDS, GAL
- **Broadcom operates a worldwide reference network**
 - live tracking of all satellites all the time
- **After the GLONASS incident, we compared the collected BE against the previously predicted LTO ...**

EPHEMERIS ERROR VS TIME (SATELLITE 1)


BE vs LTO, orbit and clock




EPHEMERIS ERROR, ALL 24 GLONASS SATELLITES, FROM ARCHIVED BE DATA OVER 7 DAYS



On this resolution and time scale and resolution (4 hours, 7 days) archived BE for SVs 6, 7, 8, 14, 15, 23 & 24 do not show errors



The GLONASS April 1st Incident in the IGS



Time scale 10 hours
Resolution ½ hour

Messages affected (from Hugentobler, E-mail April 4). Satellites 6, 7, 8, 14, 15, 23, 24 back to normal before end of April 1st (UTC).

International Association of Geodesy



3-Jun-14

12

Courtesy: Gerhardt Beutler, Astronomical Institute, University of Bern

“There were some mathematical mistakes, but they have been corrected,”
Oleg Ostapenko, head of the Russian space agency Roscosmos, 24 April 2014

From IGS analysis:

“Erroneous GLONASS Broadcast positions show a consistent rotation of about 0.5 degrees about inertial x-axis.”

Speculation ...

Maybe this species of bug?

```
#define ROUND(x) ((int) (double)x+0.5) )
```

<http://en.ria.ru/russia/20140424/189350346/Glonass-Failure-Caused-by-Faulty-Software--Roscosmos.html>

<http://gpsworld.com/the-system-glonass-in-april-what-went-wrong/> (Beutler)

<http://www.gps.gov/governance/advisory/meetings/2014-06/beutler1.pdf>

WHAT ABOUT ALERTS, HEALTH BITS, ETC?

← → ↻ <https://glonass-iac.ru/en/> ☆ 🖨 ☰




FEDERAL SPACE AGENCY

INFORMATION-ANALYTICAL CENTRE




Main
GLONASS SCC
GLONASS
GPS
News
Archive
Guide
Feedback
About IAC
UTC+3: 02:26:05

SC operability



Instant availability



GLONASS news

18.08.2014 According to GLONASS System Control Center between 13:00 on 18 August 2014 and 01:00 on 19 August 2014 activities aimed at updating GLONASS Time

Welcome to the Information-analytical centre official website!

The Website contains:


- Official information of the [GLONASS SCC](#)
- information about [GLONASS](#) and [GPS](#) operability
- precise [ephemeris](#), [GLONASS](#) and [GPS almanacs](#)
- [GLONASS](#) and [GPS bulletins](#)
- links to the sites about [GLONASS equipment](#), [navigation maps](#), russian and international [organizations](#).

GLONASS constellation status, 28.10.2014

Total satellites in constellation	28 SC
Operational	24 SC
In commissioning phase	-
In maintenance	-
Under check by the Satellite Prime Contractor	1 SC
Spares	2 SC
In flight tests phase	1 SC

Evaluation of GNSS characteristics

Суточные СКП SISRE ГЛОНАСС, м







Map Satellite

HEALTH FLAGS

From Russian Federal Space Agency Information-Analytical Center website:



→ New almanac was not broadcast during this period


→ "Error (URE > 75M)" are observed error estimates, not broadcast URE

→ Unhealthy flag was never set on any of the satellites with bad ephemeris

From Broadcom Worldwide Reference Network, received ephemeris archive:

Health bits received from all GLONASS satellites throughout this time period.


No unhealthy flags.



Time scale 24 hours

Resolution 15 minutes →

The GLONASS April 1st Incident in the IGS




Messages affected (from Hugentobler 8, 14, 15, 23, 24 back to normal by 20:00 UTC)

International Association of Geodesy

3-Jun-14

12

The GLONASS April 1st Incident in the IGS



Epilogue: At the time of transition “back to normal” the satellites were visible (with an elevation of >20 deg) from at least one of the Command Tracking Sites on Russian Territory.

International Association of Geodesy

3-Jun-14

37



BROADCAST ALMANAC, FROM THE TIME OF INCIDENT




Broadcom database of all received broadcast almanac during this incident shows no almanac health bits set unhealthy at any time for any satellite.

```
select * from [WWRN].[dbo].[GlonassRawAlmanacArchive] where created > '2014-03-30 00:00:00' and created < '2014-04-02 23:30:00'
```

	created	tauGPS	N4	NA	nA2	HNA	lambdaNA	TLambdaNA	deltaNA	deltaTNA	deltaTDotNA	EpsilonNA	OmeganA	MNA	tauNA	CNA	Ln
1	2014-03-30 21:02:31.290	-428	5	821	1	1	55204	545286	7334	-1359814	-9	445	1656	1	43	1	0
2	2014-03-30 21:02:31.317	-428	5	821	2	28	-65541	703671	10077	-1359807	-9	1320	-20705	1	-17	1	0
3	2014-03-30 21:02:31.343	-428	5	821	3	5	-188542	867106	9099	-1359817	-9	1314	-19384	1	-3	1	0
4	2014-03-30 21:02:31.373	-428	5	821	4	6	-313999	1031251	9215	-1359800	-9	421	-18194	1	-17	1	0
5	2014-03-30 21:02:31.400	-428	5	821	5	1	-437171	1192158	7263	-1359835	-9	466	12169	1	42	1	0
6	2014-03-30 21:02:31.427	-428	5	821	6	28	422804	61606	7226	-1359780	-12	878	24568	1	-11	1	0
7	2014-03-30 21:02:31.453	-428	5	821	7	5	304353	219373	9145	-1359792	-13	1113	-19159	1	23	1	0
8	2014-03-30 21:02:31.480	-428	5	821	8	6	182640	379229	9188	-1359806	-9	1895	-13158	1	6	1	0
9	2014-03-30 21:02:31.510	-428	5	821	9	30	799642	491218	12334	-1359840	3	2607	3778	1	-2	1	0
10	2014-03-30 21:02:31.537	-428	5	821	10	25	680588	646110	16945	-1359807	3	1660	27419	1	4	1	0
11	2014-03-30 21:02:31.563	-428	5	821	11	0	554839	808909	14727	-1359816	3	2048	981	1	5	1	0
12	2014-03-30 21:02:31.593	-428	5	821	12	31	430751	976251	12320	-1359834	3	3491	29227	1	11	1	0
13	2014-03-30 21:02:31.620	-428	5	821	13	30	302529	1140379	14652	-1359807	3	786	14921	1	113	1	0
14	2014-03-30 21:02:31.660	-428	5	821	14	25	-927249	2403	16861	-1359709	1	1614	27077	1	0	1	0
15	2014-03-30 21:02:31.690	-428	5	821	15	0	1045838	165446	16850	-1360002	3	2497	-629	1	-4	1	0
16	2014-03-30 21:02:31.717	-428	5	821	16	31	919375	333450	12227	-1359796	3	2155	25590	1	-4	1	0
17	2014-03-30 21:02:31.743	-428	5	821	17	4	-552849	431498	11232	-1359921	0	1337	-21068	1	-28	1	0
18	2014-03-30 21:02:31.773	-428	5	821	18	26	-541928	423817	11644	-1360472	3	1826	-1626	1	8	1	0

... continues for 72 rows and 24 hours

TRI-BAND FRONT END



Three independent system, if one system goes bad, it is easy to identify.

HOW MULTI-GNSS SAVED THE DAY

P272 - UTC 02/04/2014 02:56:37.0

SV Count: 18 EA: 8m HDOP: 1.1 VDOP: 2.0

	GPS						SBAS			ГЛОНАСС						BeiDou												
ALM ID	12	14	15	18	21	22	24	25	26	129	137	1	2	8	10	11	12	13	1	1	3	4	6	7	9	10	13	14
SVID	12	14	15	18	21	22	24	25	26	42	50	60	55	65	52	59	58	57	66	81	83	84	86	87	89	90	93	94
EL	33	25	36	81	25	45	65	13	0	44	43	72	39	24	12	65	54	2	42	45	42	34	75	65	71	38	1	51
AZ	140	285	78	263	217	309	44	173	84	159	152	69	328	123	30	34	205	209	181	159	205	133	163	234	304	232	314	313
dBHz	27	20	27	21	21	30	38	18	--	--	--	35	--	25	--	--	--	27	27	--	24	21	31	27	23	--	24	

course=69° speed=30.7 km/hr

latitude=37.49929°, longitude=127.03231°, altitude=55m

GLONASS Satellites
isolated, not used

BeiDou Satellites
used in good solution

TOOL ver. Wed Jan 29 16:38:17 PST 2014, © Broadcom

P132 - UTC 02/04/2014 02:54:13.0


SV Count: 6 EA: 11m HDOP: 1.1 VDOP: 0.9

	GPS						SBAS			ГЛОНАСС								
ALM ID	12	14	15	18	21	22	24	25	26	128	129	1	2	8	10	11	12	13
SVID	12	14	15	18	21	22	24	25	26	41	42	60	55	65	52	59	58	57
EL	30	23	35	79	24	42	64	11	--	--	--	71	37	24	11	65	52	1
AZ	139	282	75	270	217	307	43	172	--	--	--	63	327	120	29	35	203	208
dBHz	30	32	35	25	23	36	20	13	--	31	30	25	38	28	21	25	25	--

course=24° speed=0 km/hr

latitude=37.49313°, longitude=127.03026°, altitude=88m

GLONASS Satellites
used in bad solution



Map

UTC Time : May 20, 2014 3:03:13 AM
 Lat : 53.08077750 Accuracy : 6.0 m
 Lon : 171.69181212 Speed : 956.45 km/h
 Alt : 10694.39 m Bearing : 267.31845
 In Use : 16 TTF : 9.30 sec.
 In View : 16 Elapsed Time : 01:22

UTC Time : May 20, 2014 4:42:00 AM
 Lat : 46.13707304 Accuracy : 6.0 m
 Lon : 154.68443713 Speed : 855.08 km/h
 Alt : 10681.77 m Bearing : 229.64496
 In Use : 18 TTF : 17.80 sec.
 Elapsed Time : 00:32


UTC Time : May 21, 2014 1:10:38 PM
 Lat : 32.06149548 Accuracy : 8.0 m
 Lon : 118.77931692 Speed : 0.00 km/h
 Alt : 20.80 m Bearing : 0.0
 In Use : 24 TTF : 0.95 sec.
 In View : 28 Elapsed Time : 00:11

UTC Time : May 21, 2014 5:30:54 PM
 Lat : 48.6732 Accuracy : 8.0 m
 Lon : 124.8629 Speed : 0.00 km/h
 Bearing : 0.0
 TTF : 62.86 sec
 Elapsed Time : 17:35



Availability of 4 or more BeiDou satellites,
above 10° horizon mask angle


四颗以上，水平仰角大于10度的北斗卫星
的可获性



Availability of 4 or more BeiDou satellites,
above 10° horizon mask angle

17 May 2013

四颗以上，水平仰角大于10度的北斗卫星的
可获得性



- **GLONASS failure was caused by wrong Broadcast Ephemeris**
- **It affected all satellite orbits (but not clocks)**
- **IGS identified the error as an erroneous rotation of the orbital planes about the inertial x-axis**
- **Error identified almost immediately by the GLONASS operators ...**
- **... but not communicated to users through broadcast health bits in broadcast ephemeris or broadcast almanac**
- **Commercial consumer LTO system (Broadcom) and Scientific system (IGS) show consistent data w.r.t duration and magnitude of errors and broadcast health bits**
- ✓ **Consumer products with GPS, GLONASS, QZSS and BeiDou operated seamlessly through the incident.**
- ✓ **With the addition of Galileo, this kind of robustness will be possible worldwide.**